

SURFACE DOWNLIGHT

10W 154mm 3000K IP20 CRI90 DALI



ΠΕΡΙΕΧΟΜΕΝΑ / CONTENTS

SKU: AG010104-006

DATASHEET 1
 MANUAL 2

DATASHEET



GENERAL INFORMATION

APPLICATION	Indoor
DIRECTION OF MOUNTING	Ceiling
VISIBLE DIMENSIONS (Ø×L)	Ø75 × 154 mm
MATERIAL	Aluminium
COLOR	White
IP PROTECTION	IP20
LED	Bridgelux LED
WATTAGE	10W
VOLTAGE	230VAC
BEAM ANGLE	26D
CCT	3000K
CRI	Ra>90
DIMMABLE	DALI
WARRANTY	2 years
ORIGIN	China

SURFACE DOWNLIGHT

10W 154mm 3000K IP20 CRI90 DALI MANUAL

ΟΔΗΓΙΕΣ ΕΓΚΑΤΑΣΤΑΣΗΣ INSTALLATION INSTRUCTIONS

ΣΗΜΑΝΤΙΚΟ:

Αυτό το εξάρτημα πρέπει να εγκατασταθεί από εξειδικευμένο ηλεκτρολόγο.

Η BarisLight δεν φέρει ευθύνη για τυχόν ζητήματα που προκύπτουν από ακατάλληλη εγκατάσταση που δεν συμμορφώνεται με τα τοπικά πρότυπα ασφαλείας.

Παρακαλούμε δώστε ένα αντίγραφο αυτών των οδηγιών στο άτομο που είναι υπεύθυνο για τη συντήρηση της εγκατάστασης.

IMPORTANT:

This luminaire must be installed by a qualified electrician.


Disclaimer:

BarisLight is not liable for any issues arising from improper installation that does not comply with local safety standards.

Instructions:

Please provide a copy of these instructions to the person responsible for maintaining the installation.

Σύνδεση με την ηλεκτρική παροχή Connection to the electrical supply



Διαδικασία καλωδίωσης

1. Κλείστε τον κεντρικό διακόπτη ρεύματος.
2. Συνδέστε τα φωτιστικά στη μονάδα παροχής ρεύματος.
3. Συνδέστε τη μονάδα τροφοδοσίας στο ηλεκτρικό δίκτυο.
4. Ενεργοποιήστε τον κεντρικό διακόπτη ρεύματος.

Σημείωση ασφαλείας: Βεβαιωθείτε ότι ο κεντρικός διακόπτης λειτουργίας είναι απενεργοποιημένος κατά τη διάρκεια όλων των διαδικασιών συντήρησης και εγκατάστασης.

Προειδοποίηση: Αποφύγετε τη σύνδεση πάρα πολλών φωτιστικών παράλληλα σε μία μόνο μονάδα τροφοδοσίας για να αποφευχθεί η υπερφόρτωση.

Wiring Procedure

1. Turn off the main power switch.
2. Connect the luminaires to the power supply unit.
3. Connect the power supply unit to the electrical network.
4. Turn on the main power switch.

Safety Notice: Ensure the main power switch is turned off during all maintenance and installation procedures.

Warning: Avoid connecting too many luminaires in parallel to a single power supply unit to prevent overloading.

SURFACE DOWNLIGHT

10W 154mm 3000K IP20 CRI90 DALI MANUAL

Τοποθέτηση Installation

